



HPATX

The High Power Alarm Transmitter

The ideal external alarm extension for far remote areas, the High Power Alarm Transmitter, encased in a durable, waterproof casing, works in exactly the same manner as a Remote Control Transmitter

however, it has a hard wire input trigger that can be connected to devices such as a low current consumption Passive Infra Red

Detectors or a Magnetic Contact. When the circuit is opened (or closed depending on the connection) the High Power Alarm Transmitter will automatically send a signal.

The High Power Alarm Transmitter can operate on a 9 or 12 V DC adapter. With a superb transmission range of up to 1km the HPATX makes those far-off, hard to reach places reachable.



Features:

Up to 500m (line of sight) when used
with any Standard Bartronics
Receiver

Up to 1km (line of sight)
when used with any
External Bartronics
Receiver

HPATX

The High Power Alarm Transmitter

Dimensions:

Length: 11cm

Width: 8.5cm

Depth: 2.8cm

Specifications:

CURRENT CONSUMPTION:

8.8 mA at 12V

STANDARD CURRENT CONSUMPTION:

5 uA

ERP:

11.0 mW

FREQUENCY:

403.55 Mhz

433.92 Mhz

and others on request

BATTERY VOLTAGE:

9V or 12V

CODING SEQUENCE:

9 Bit Trinary

NUMBER OF CODES AVAILABLE:

19683



Tel: +27 (0)11 396 2720 / 0861 BARTRON

Fax: +27(0)11 396 2727

Web: www.bartronics.co.za

38 Pomona Road, Pomona Estates, Kempton Park

GPS Co-ordinates: S 26 05.362 E 28 16.407

P.O. Box 12188

Aston Manor

1630

South Africa