



1CEMR

1 Channel External Multitek Receivers (with antenna)

The 1 Channel External Multitek Receiver (with antenna) is diverse, reliable and compatible with Dyno Code Hopping Transmitters. All you ever wanted in a receiver and more!

Features:

Relay can be selected between pulse and latch

Relay rated at 5 amp, 220 volt output relay

Built in field strength LED to assist with installation

Unique advanced interference reduction circuit

Incorporates Multitek Smart Memory

Compatible with Binary, Trinary, French Rolling Code & Code Hopping



1CEMR

**1 Channel External Multitek Receivers
(with antenna)**

Dimensions:

Length: 11cm
Width: 8.5cm
Depth: 2.8cm
Antenna : 30 cm

Specifications:

TOTAL CURRENT CONSUMPTION:
6 mA + 70mA/relay
STANDBY CURRENT CONSUMPTION:
8 mA
SENSITIVITY:
1 uV
SUPPLIED VOLTAGE:
9 15V DC in Latch Mode and
9 24 AC or DC in Pulse Mode
RELAY CONTACTS:
5 amp
RELAY CONTACTS VOLTAGE:
220V AC
FREQUENCY:
403.55 Mhz
433.92 Mhz
and others on request



Tel: +27 (0)11 396 2720 / 0861 BARTRON

Fax: +27(0)11 396 2727

Web: www.bartronics.co.za

38 Pomona Road, Pomona Estates, Kempton Park

GPS Co-ordinates: S 26 05.362 E 28 16.407

P.O. Box 12188

Aston Manor

1630

South Africa